



Order Code 40366
Description DWL 32W 75° C90 IP54 BI RD 3K
Code 103040366
Driver Code 530462000
Current Default (Max) 800 mA
Number of Drivers 1



ADJUSTMENT OF THE POWER OF THE APPLIANCES BY MEANS OF THE DIP SWITCH

| Current mA | Power % | Switch Positions | | | |
|------------|-------------|------------------|-----------|------------|-----------|
| | | 1 | 2 | 3 | 4 |
| 300 | 38% | OFF | OFF | OFF | OFF |
| 350 | 44% | ON | OFF | OFF | OFF |
| 400 | 50% | OFF | ON | OFF | OFF |
| 450 | 56% | ON | ON | OFF | OFF |
| 500 | 63% | OFF | OFF | ON | OFF |
| 550 | 69% | ON | OFF | ON | OFF |
| 600 | 75% | OFF | ON | ON | OFF |
| 650 | 81% | ON | ON | ON | OFF |
| 700 | 88% | OFF | OFF | OFF | ON |
| 750 | 94% | ON | OFF | OFF | ON |
| 800 | 100% | OFF | ON | OFF | ON |
| 850 | - | - | - | - | - |
| 900 | - | - | - | - | - |
| 950 | - | - | - | - | - |
| 1000 | - | - | - | - | - |
| 1050 | - | - | - | - | - |